



ASSEMBLY MANUAL

XTRMB01 Xtreme Standing workstation

WE ENCOURAGING YOU WATCHING STEP BY STEP VIDEO MANUALS

For XTREME step by step assembly manual on You tube scan code on the right





For Pull out keyboard assembly manual on You tube scan code on the right



NOTE:

Please assemble your product on soft surface to avoid scratches and damages on lacquer.




Thank you for making StudioDesk your desk of choice!









Before beginning assembly of your stand, let's get familiar with the parts you have received in your package. Please match the corresponding numbers on this page with the drawings.

Parts

1. Motorized Electric legs
2. Bottom desk surface
3. Spacer desk surface
4. Top desk surface
5. Top shelf
6. Padded armrest



Hardware

<p>⑥ M6 Screw 8 pcs</p> 	<p>⑦ Pillars 4 pcs</p> 	<p>⑧ Screws for wood 2 pcs 4 x 20</p> 
<p>⑨ Rackrail (optional) 2 pcs</p> 	<p>⑩ Wooden dowel 4 pcs</p> 	<p>⑪ USB HUB 1 pc</p> 
<p>⑫ Long screws M6 4 pcs</p> 	<p>⑬ Controller 1 pc</p> 	



Tools needed (Not included)



1

Step One

Place bottom desk surface on the floor. Place U profiles as shown on the illustration on it and make sure that central bigger holes are facing towards out. Screw them with M6 screws included in the set.



2



Step Two

Place Central support as shown on the illustration.

3

Step Three

Make sure that central part is inserted evenly on both sides.



4



Step Four

Fix central part to the desk surface using M6 screws. Fix central support using M6 screws.

5

Step Five


Add columns with electric motors as shown on the illustration and fix it with M6 Screws. Do the same on the both sides.



6



Step Six

Put on foots to the columns and fix it as shown on the illustration.




7

Step Seven






8

Step Eight



9

Step Nine



10

Step Ten






Install optional pull out holders as shown in the illustration using M6 screws. Scancode for more detailed video about installing pull out option.

11

Step Eleven

Turn desk in standing position. Install wooden dowels as shown on the illustration and install Spacerdesk surface on the top.



12


Step Twelve

Carefully stick included long LEDstrip to the Spacersurface as shown on the illustration.

13

Step Thirteen

Install armrest to the main desk surface using screws for wood. Once armrest is in the place, install main desk surface on the top of the middle desk surface as shown on the illustration on the right.



14



Step Fourteen

Carefully remove the glass from the main desk surface and install shorter LED strip as shown in the illustration. Connecting cable should go out through the hole towards down. Carefully put the glass back in the place.

15

Step Fifteen

If you purchase optional rack rails option, now is the time to screw it in the place using M6 screws.



16

Step Sixteen

Place the pillars on the positions so the long screws (13) can pass through all three desk surfaces, pillars (7) and end in the top shelf (5).

Fasten long screws using wrench tool.

Note! Washers should be used from the bottom.

17

Step Seventeen

As the last step, install USBhub cable inlay to your desk and connect it to your computer.

